

FaceRig

In order to start FaceRig, you have to doubleClick SteamLogin_FaceRig on the Desktop. Then you need to go to



and select "FaceRigStudio Personal"

Connecting with RunCam 2 (IP Camera)


http://runcam.com/images/11_03-05.png

Manual

1. Switch on RunCam Camera until Powerbutton lights up blue 2. Press WiFi Button until Wifi-Led blinks blue 3. Start WLAN and select RUNCAM2_846eb6 (or something similar) 4. Enter Password 1234567890

→ Wifi-Led stops blinking

5.FaceRigStudio > Advanced UI> Advanced Tracking Configuration > Input Device 6. Input Type > IP Camera 7. IP Camera URL > rtsp:192.168.1.1:554/MJPEG?W=720&H=400&Q=50&BR=5000000/track1 8. Connect ===== Connecting with Axio Neuron =====

<https://www.youtube.com/watch?v=oOwaeGcOOc4> ===== Streaming Avatar =====  You need to have installed: - OBS (Open Broadcasting Software) - OBS->NDI - NDI->Spout - Spout - Select "Broadcast" inside FaceRig - Open OBS (Open Broadcasting Software) - Create "Source/Quelle" → + → VideoRecording Device → select "FaceRig Virtual Camera" - RightClick new Source → Filter - Add Chroma Key - Menu→Tools/Werkzeuge→NDI-OutputSettings - Start NDI to Spout Application - Select NDI source - Open Spout Receiver

From:

<https://wiki.zhdk.ch/IASpace/> - **immersive art space**

Permanent link:

<https://wiki.zhdk.ch/IASpace/doku.php?id=facerig&rev=1526651786>

Last update: **2018/05/18 15:56**

