FaceRig

In order to start FaceRig, you have to doubleClick SteamLogin_FaceRig on the Desktop. Then you need to go to

and select “FaceRigStudio Personal”

Connecting with RunCam 2 (IP Camera)

Manual

1. Switch on RunCam Camera until Powerbutton lights up blue
2. Press WiFi Button until Wifi-Led blinks blue
3. Start WLAN and select RUNCAM2_846eb6 (or seomthing similar)
4. Enter Password 1234567890
5. Wifi-Led stops blinking
6. FaceRigStudio > Advanced UI> Advanced Tracking Configuration > Input Device
7. Input Type > IP Camera
8. IP Camera url > rtsp://192.168.1.1:554/MJPG?W=720&H=400&Q=50&BR=5000000/track1
9. Connect.

Connecting with Axio Neuron

https://www.youtube.com/watch?v=oOwaeGcOOc4

Streaming Avatar

You need to have installed:

1. OBS (Open Broadcasting Sofware)
2. OBS->NDI
3. NDI->Spout
4. Spout

1. Select “Broadcast” inside FaceRig
2. Open OBS (Open Broadcasting Sofware)
3. Create “Source/Quelle” → + → VideoRecording Device → select “FaceRig Virtual Camera”
4. RightClick new Source → Filter
5. Add Chroma Key
6. Menu→Tools/Werkzeuge→NDI-OutputSettings

7. Start NDI to Spout Application
8. Select NDI source
9. Open Spout Receiver

From:
https://wiki.zhdk.ch/IASpace/ - **immersive art space**

Permanent link:
https://wiki.zhdk.ch/IASpace/doku.php?id=facerig&rev=1526652075

Last update: **2018/05/18 16:01**