

# FaceRig

In order to start FaceRig, you have to doubleClick SteamLogin\_FaceRig on the Desktop. Then you need to go to



and select "FaceRigStudio Personal"

## Connecting with RunCam 2 (IP Camera)



Manual

1. Switch on RunCam Camera until Powerbutton lights up blue
2. Press WiFi Button until Wifi-Led blinks blue
3. Start WLAN and select RUNCAM2\_846eb6 (or seomthing similar)
4. Enter Password 1234567890
5. Wifi-Led stops blinking
6. FaceRigStudio > Advanced UI> Advanced Tracking Configuration > Input Device
7. Input Type > IP Camera
8. IP Camera url >  
**rtsp://192.168.1.1:554/MJPEG?W=720&H=400&Q=50&BR=5000000/track1**
9. Connect.

## Connecting with Axio Neuron

<https://www.youtube.com/watch?v=oOwaeGc00c4>

## Streaming Avatar



You need to have installed:

1. [OBS \(Open Broadcasting Software\)](#)
  2. [OBS->NDI](#)
  3. [NDI->Spout](#)
  4. [Spout](#)
1. Select "Broadcast" inside FaceRig
  2. Open OBS (Open Broadcasting Software)
  3. Create "Source/Quelle" → + → VideoRecording Device → select "FaceRig Virtual Camera"
  4. RightClick new Source → Filter
  5. Add Chroma Key

6. Menu→Tools/Werkzeuge→NDI-OutputSettings
7. Start NDI to Spout Application
8. Select NDI source
9. Open Spout Receiver

From:

<https://wiki.zhdk.ch/IASpace/> - **immersive art space**

Permanent link:

<https://wiki.zhdk.ch/IASpace/doku.php?id=facerig&rev=1526652088>

Last update: **2018/05/18 16:01**

